

# YAKKER

2 Port NMEA to WiFi Bridge  
www.yakbitz.com

Once powered up the YAKKER creates a WiFi hotspot. Connect to this with your Wifi Phone/Tablet etc using the default password of 12345678.

Next start your browser and enter 192.168.5.1 into the address bar to access the setup screen shown in Fig. 1.

## Operating Mode

The yakker can operate as an Access Point which creates a private network to which you connect your WiFi enabled devices such as a smartphones, PCs or tablets. This is the factory default mode.

The yakker can also connect to your existing WiFi network so your devices can access the NMEA data broadcast by the Yakker and also access resources of your network such as the internet or a printer.

**N.B.** If the Yakker cannot connect to your router pressing the reset button will reboot it in Access Point mode.

## Protocol

The Yakker can send your NMEA data over WiFi using either UDP or TCP protocols as required by your navigation software. UDP is the default factory setting.

## Transmit Power

You can adjust the transmit power of the Yakker according to the range required.

## Baud Rate

The baud rate is the speed that your NMEA equipment such as your AIS receiver, GPS, Sounder uses to export its data. Refer to your equipment's user to determine the speed that is used.

\*\*Each port can be set to any speed, but it is recommended that Rx2 be set to the higher speed.

## Reset Button

Pressing the reset button reboots the Yakker in Access Point mode. Press and hold the reset button until the green light starts blinking (approx 5 sec.) to reset the Yakker to factory default settings.

The screenshot shows a mobile browser interface for the YAKKER setup page. The address bar shows '192.168.5.1'. The page title is 'YAKKER by YAKBITZ 2 Port NMEA to WiFi Bridge'. The main heading is 'Enter new connection details and hit Submit WiFi'. There are three radio button options: 'Create Access Point' (selected), 'Connect to Router/AP', and 'UDP Mode' (selected). Under 'Create Access Point', the SSID is 'Yakker' and the PWD is '12345678'. Under 'Connect to Router/AP', the SSID is 'YourNetwork' and the PWD is 'YourPassword'. Under 'UDP Mode', the UDP Port is '2000'. Under 'TCP Mode', the TCP Port is '23'. The 'Transmit Power' is set to 'LOW'. At the bottom, there is an 'NMEA' section with two columns of radio buttons for 'Rx1' and 'Rx2', with speeds 4800, 9600, 19200, and 38400. The 'Submit' button is at the bottom right.

Fig. 1